

AGRI 200 ENERGIZER



The Agri 200 energizers can be powered by mains adaptor or solar with battery using additional solar conversion kit (sold separately).

Features:

- Powers up to 200km (optimal conditions) and 56km (average conditions) of fence wire*
- Robust weather-resistant system with lightning protection
- Easy-to-use tag included to switch energizer on and off
- Output energy max 20J (stored energy 29J)
- Powered by mains adaptor or solar with battery using additional solar conversion kit (sold separately)
- Programmable and controllable via the [Nemtek Connect](#) app: program, control, and monitor features such as adjustable fence voltage and pulse rate, adjustable energizer fence overload indicators and alarms, accurate battery and fence voltage reporting, battery type selection, safety level control, and battery-saving modes.

Specifications:

Dimensions	431.54(L) x 280.83(W) x 140(D)mm
Output energy max	20J (stored energy 29J)
Output voltage	9.5kV @ 1000Ohms
Power source	Battery 12Vdc Power supply 12Vdc
IP rating	IP65

Stock Code	Description
AE-AGRI200	Agri 200 Energizer